

Revision Date: 12/20/2024

Subject: E447 Error Code

Models: DVM, CHILLER

Title: Fan Motor 1 Not Connected to Outdoor Unit

Fan 1 is on the left-hand side of the unit

Troubleshooting Steps: Condenser with 2 Fans

1. Remove power to the condensing unit for a minimum of 15 minutes.
2. Inspect the fan blade and make sure there are no obstructions.
3. Verify blade spins freely.
4. There are two plug connections for each fan motor. Power (red, white, and black) and hall effect sensor. (See Fan Motor Connector Image)
5. Follow and inspect wiring. Make sure there is no damage to wires or plugs.
6. Make sure all plugs and spade connectors are secure and connected properly.
7. Disconnect power plug (Fan motor 1 is white plug, Fan motor 2 is blue plug) Check resistance at plug going to Fan motor. Red-White, Red- Black and White to Black. The resistance value between each winding should be equal, under 10Ω and open to ground.
8. Reverse connector plugs for Fan motor 1 and Fan motor 2. (Fan Motor and Hall Effect plug)
9. Restore power to the unit. If the E447 error returns, replace fan PCB. If the error changes to E347, replace the fan motor.

If results are inconclusive, and you have an inverter checker tool, continue to inverter Fan PCB test.

10. Remove power from the unit for a minimum of 15 minutes. Remove Fan connections from Fan PCB and connect inverter checker.
11. Restore power to unit. Press K2 button 11 times to initiate the inverter test for fan motor 1.
12. If the inverter test fails, replace Fan PCB. If it passes, replace Fan motor



Fan #1 is on the left-hand side of unit

See the Video showing this troubleshooting technique. Click the icon below:



FAN Motor Connector



Hall-sensor Connector

Troubleshooting Steps: Condenser with 1 Fan

1. Turn the power to the system off and wait 15 minutes.
2. Inspect the fan blade and make sure there are no obstructions.
3. Verify blade spins freely.
4. There are two plug connections for fan motor. Power (red, white, and black) and hall effect sensor.
5. Follow and inspect wiring. Make sure there is no damage to wires/plugs.
6. Make sure all plugs and spade connectors are secure and connected correctly.
7. Unplug power plug (Fan motor1 is white plug) Ohm out connections. U-V, U-W, V-W. The resistance value between each winding should be equal, under 10Ω and open to ground.
8. If all values are within range, remove fan connections from board and connect inverter checker to Fan PCB.
9. Press K2 button 11 times to initiate the inverter test for fan motor 1. Inverter test video
10. If the inverter test fails, replace Fan PCB. If it passes, replace fan motor.

See the Video showing this troubleshooting technique. Click the icon below:



**** Before reconnecting any wire harnesses, leave the unit powered OFF for 15 – 20 min****